

Parameter estimation
for an Ornstein Uhlenbeck process
with a periodic in time drift

Dominique Dehay

Université Rennes 2

email : dominique.dehay@univ-rennes2.fr

Introduction

Discrete time : PAR(1) model (Gladyshev 1961, Paggano 1978, Vecchia 1985, Hurd, Makagon & Miamee 2002)

$$\xi_{k+1} = \phi_k \xi_k + \epsilon_k \quad \text{where} \quad \phi_{k+T} = \phi_k$$

$$\xi_{k+1} - \xi_k = \theta_k \xi_k + \epsilon_k \quad \theta_k = \phi_k - 1$$

Continuous time model :

$$d\xi_t = \theta f(t) \xi_t dt + dW_t \quad f(t+T) = f(t)$$

Examples :

$$d\xi_t = \theta \sin(t) \xi_t dt + dW_t \quad f(t) = \sin(t)$$

$$d\xi_t = \theta (\sin(t) - 0.5) \xi_t dt + dW_t \quad f(t) = \sin(t) - 0.5$$

$$d\xi_t = \theta (\sin(t) + 0.5) \xi_t dt + dW_t \quad f(t) = \sin(t) + 0.5$$

Höpfner & Kutoyants (2009): Estimating discontinuous periodic signal

$$d\xi_t = [S(\theta, t) + b(\xi_t)]dt + \sigma(\xi_t)dW_t$$

periodic drift $t \mapsto S(\theta, t) = \lambda(t) + \lambda^*(t)\mathbb{I}_{(\theta, \theta+a)}(i_T(t))$,

with $i_T(t) = t [T]$

$b(\cdot)$ and $\sigma(\cdot)$ are Lipschitz

T -periodic semi-group

Let $(\xi_t)_{t \geq 0}$ Markov process with continuous paths, inhomogeneous in time with T -periodic semigroup density

$$(P_{s,t}(x, dy) = p_{s,t}(x, y)dy)$$

$$p_{s,t}(x, y) = p_{s+kT, t+kT}(x, y) \quad \text{for all } k \in \mathbb{N}^*, 0 \leq s, t < \infty.$$

$\xi = (\xi_t)_{t \in \mathbb{R}^+}$ continuous Markov process

→ induced Markov chain $\mathbf{X} = (X_k)_{k \in \mathbb{N}}$, $X_k := (\xi_{kT+s})_{0 \leq s \leq T}$.

chain of T -segments in the paths of ξ

The state space of the Markov chain X is the space $C[0, T]$ of continuous functions defined on $[0, T]$.

The chain X is time homogeneous with one-step-transition kernel

$$Q(\alpha, F) = P \left[(\xi_s)_{0 \leq s \leq T} \in F \mid \xi_0 = \alpha(T) \right], \quad \alpha \in C[0, T], \quad F \in \mathcal{C}_T.$$

Example . With $\sigma > 0, \gamma > 0$ and some function $S(\cdot)$ which is T -periodic and piecewise continuous, consider Ornstein-Uhlenbeck type diffusion with T -periodic drift

$$d\xi_t = (S(t) - \gamma\xi_t)dt + \sigma dW_t.$$

Solution with initial value ξ_0

$$\xi_t = \xi_0 e^{-\gamma t} + \int_0^t e^{-\gamma(t-s)} (S(s) ds + \sigma dW_s).$$

Transition semigroup density of ξ

$$p_{s,t}(x, \cdot) = \mathcal{N} \left(x e^{-\gamma(t-s)} + \int_0^{t-s} e^{-\gamma v} S(t-v) dv, \frac{1 - e^{-2\gamma(t-s)}}{2\gamma} \sigma^2 \right)$$

Orstein Uhlenbeck model with periodic in time drift

$$d\xi_t = f(t)\xi_t dt + dW_t$$

where $f(\cdot)$ is some known T -periodic function

Deterministic equation

$$x'(t) = f(t)x(t), \quad x(t) = x_0 \exp \left\{ \int_0^t f(s) ds \right\} = x_0 \exp\{F(t)\}$$

$$F(t) = \int_0^t f(s) ds = n_t F(T) + F(t - n_t T), \quad n_t = \text{integer part of } \frac{t}{T}.$$

If $F(T) = \int_0^T f(t) dt = 0$ then $x_t = x_{t+kT}$ for any $k \in \mathbb{N}$

Otherwise

$$\lim_{t \rightarrow \infty} |x_t| = \begin{cases} 0 & \text{if } F(T) < 0 \\ \infty & F(T) > 0 \end{cases} \quad (\text{when } x_0 \neq 0).$$

$$d\xi_t = f(t)\xi_t dt + dW_t$$

Solution

$$\xi_t = x_{0,t} \left(\xi_0 + \int_0^t x_{0,s}^{-1} dW_s \right) = x_{0,t} \xi_0 + \int_0^t x_{s,t} dW_s$$

where

$$x_{0,t} = \exp \left\{ \int_0^t f(u) du \right\} = \exp\{F(t)\} \quad 0 \leq s < t < \infty$$

First property

$$(x_{0,t})^{-1} \xi_t - \xi_0 = \int_0^t (x_{0,s})^{-1} dW_s$$

so $\{(x_{0,t})^{-1} \xi_t - \xi_0 : t \geq 0\}$ is a zero-mean martingale

Markov properties

Transition semigroup density of ξ

$$p_{s,t}(x, \cdot) = \mathcal{N} \left(x_{s,t}, \int_s^t x_{u,t}^2 du \right)$$

T -periodic semigroup :

$$p_{s+T,t+T}(x, \cdot) = p_{s,t}(x, \cdot)$$

Chain of T -segments on $C[0, T]$: $\mathbf{X}_k := (\xi_{kT+t})_{0 \leq t \leq T}$

Let $\mathbf{W}_k(t) = \int_0^t x_{s,T} dW_s^{(kT)}$ where $W_s^{(kT)} = W_{s+kT}$.

$$\begin{aligned}\xi_{t+kT} &= x_{0,T}\xi_{t+(k-1)T} + \int_0^T x_{s,t} dW_s^{(t+(k-1)T)} \\ &= x_{0,T}\xi_{t+(k-1)T} + x_{0,t} \int_t^T x_{s,T} dW_s^{((k-1)T)} + \int_0^t x_{s,t} dW_s^{(kT)}\end{aligned}$$

$t \in [0, T]$.

Then

$$\mathbf{X}_{k+1}(t) = x_{0,T}\mathbf{X}_k(t) + x_{0,t}(\mathbf{W}_k(T) - \mathbf{W}_k(t)) + x_{t,T}^{-1}\mathbf{W}_{k+1}(t)$$

If $F(T) < 0$, the chain \mathbf{X} is Harris positive recurrent (ergodic)

If $F(T) > 0$, the chain \mathbf{X} is not recurrent.

Conjecture : if $F(T) = 0$, the chain \mathbf{X} is recurrent null .

Autoregressive representation

The $C[0, T]$ -valued variable \mathbf{W}_{k+1} is independent from \mathbf{X}_k and $\mathbf{W}_k(T) - \mathbf{W}_k$. Furthermore, we can say that

$$\mathbf{Y}_{k+1} = \Phi(\mathbf{Y}_k, \mathbf{W}_{k+1}) = \mathbf{A}(\mathbf{Y}_k) + (x_{\cdot, T})^{-1} \mathbf{W}_{k+1}(\cdot),$$

where $\mathbf{Y}_k = (\mathbf{X}_k, \mathbf{W}_k)$ and

$$\mathbf{A}(\mathbf{Y}_k) = \mathbf{A}(\mathbf{X}_k, \mathbf{W}_k) = x_{0, T} \mathbf{X}_k(\cdot) + x_{0, \cdot} (\mathbf{W}_k(T) - \mathbf{W}_k(\cdot))$$

The operator \mathbf{A} is linear on $C[0, T] \times C[0, T]$ with values in $C[0, T]$, bounded for sup norm.

$(\mathbf{Y}_k)_{k \in \mathbb{Z}}$ is a Markov chain.

Asymptotics of ξ_t as $t \rightarrow \infty$ Let $G(t) = \int_0^t e^{-2F(s)} ds$

If $F(T) < 0$ then

$$\xi_{t+nT} \implies e^{F(t)} \mathcal{N}\left(0, \frac{G(T)}{e^{-2F(T)} - 1} + G(t)\right) \quad \text{as } n \rightarrow \infty, t \in [0, T]$$

If $F(T) = 0$ then

$$\frac{1}{n} \xi_{t+nT} \xrightarrow{a.e.} 0$$

$$\frac{1}{\sqrt{n}} \xi_{t+nT} \implies e^{F(t)} \mathcal{N}(0, G(T)) \quad \text{as } n \rightarrow \infty, t \in [0, T]$$

If $F(T) > 0$ then

$$e^{-nF(T)} \xi_{t+nT} \xrightarrow{a.e.} e^{F(t)} (\xi_0 + Y) \quad \text{as } n \rightarrow \infty, t \in [0, T]$$

and $Y \sim \mathcal{N}\left(0, \frac{G(T)}{1 - e^{-2F(T)}}\right)$

Parameter estimation for Ornstein-Uhlenbeck process

$$d\xi_t = \theta \xi_t dt + dw_t, \quad \xi_0 = 0, \quad t \in [0, A], \quad A \rightarrow \infty$$

Maximum likelihood estimator (MLE) $\hat{\theta}_A = \int_0^A \xi_s d\xi_s / \int_0^A \xi_s^2 ds.$

(i) $\theta < 0$: the process is positive recurrent, ergodic with invariant measure $\mathcal{N}(0, \frac{-1}{2\theta})$, and $\sqrt{A}(\hat{\theta}_A - \theta) \implies \mathcal{N}(0, 2\theta).$

(ii) $\theta = 0$: the process is null recurrent

$$\sqrt{A}(\hat{\theta}_A - \theta) = \sqrt{A}\hat{\theta}_A \implies \frac{\int_0^1 w_t dw_t}{\int_0^1 w_t^2 dt} = \frac{w_1^2 - 1/2}{\int_0^1 w_t^2 dt}$$

where $(w_t)_{0 \leq t \leq 1}$ is some standard Wiener process.

(iii) $\theta > 0$: the process is not recurrent : $|\xi_t| \rightarrow \infty$ with probability 1

$$\frac{1}{\sqrt{2\theta}} e^{\theta A} (\hat{\theta}_A - \theta) \implies \frac{\nu}{\xi^0}$$

where $\nu \sim \mathcal{N}(0, 1)$, and $\xi^0 \sim \mathcal{N}(0, \frac{1}{2\theta})$

Parameter estimation

$$d\xi_t = \theta f(t)dt + dW_t \quad \xi_0 = 0, \quad 0 \leq t \leq A$$

Solution

$$\xi_t(\theta) = x_{0,t}^\theta \left(\xi_0 + \int_0^t (x_{0,s}^\theta)^{-1} dW_s \right) = x_{0,t}^\theta \xi_0 + \int_0^t x_{s,t}^\theta dW_s$$

where

$$x_{s,t}^\theta = (x_{s,t})^\theta = \exp \left\{ \theta \int_s^t f(u) du \right\} = \exp \{ \theta (F(t) - F(s)) \} = e^{\theta (F(t) - F(s))}$$
$$0 \leq s < t < \infty$$

Here the condition is on $\theta F(T)$

Maximum likelihood estimator of θ

$$\hat{\theta}_A = \frac{\int_0^A f(t) \xi_t d\xi_t}{\int_0^A f(t)^2 \xi_t^2 dt} = \theta + \frac{\int_0^A f(t) \xi_t dW_t}{\int_0^A f(t)^2 \xi_t^2 dt}$$

1) If $\theta F(T) < 0$ then

$$\lim_{A \rightarrow \infty} \frac{1}{A} \int_0^A f(t)^2 \xi_t^2 dt \xrightarrow{\text{a.e.}} \frac{-G_\theta(T)}{T(1 - e^{-2\theta F(T)})} \int_0^T f(t)^2 dt + \frac{1}{T} \int_0^T f(t)^2 G_\theta(t) dt = \sigma_{\theta,1}^{-2}$$

$$\sqrt{A}(\hat{\theta}_A - \theta) \implies \mathcal{N}(0, \sigma_{\theta,1}^2)$$

2) If $\theta F(T) > 0$ then

$$(x_{0,t})^{-2} \xi_t^2 \xrightarrow{\text{a.e.}} Y_\theta^2$$

$$e^{n\theta F(T)} (\hat{\theta}_{nT} - \theta) \implies \frac{\mathcal{N}(0, \sigma_{\theta,2}^2)}{|Y_\theta|}$$

where $\sigma_{\theta,2}^{-2} = \frac{e^{2\theta F(T)} - 1}{\int_0^T e^{2\theta F(t)} f(t)^2 dt}$

3) If $\theta = 0 : \xi_t = W_t$

$$\sqrt{A}(\hat{\theta}_A - \theta) = \sqrt{A}\hat{\theta}_A \implies \frac{\int_0^1 w_t dw_t}{\int_0^1 w_t^2 dt} = \frac{w_t^2 - 1/2}{\int_0^1 w_t^2 dt}$$

where $(w_t)_{0 \leq t \leq 1}$ is some standard Wiener process.

4) If $F(T) = 0$ open problem

References

- H.M. Dietz & Y. Kutoyants (2003), Parameter estimation for some non-recurrent solutions of SDE, *Statistics & Decisions*, 29–45.
- R. Höpfner & Y. Kutoyants (2010), On LAN for parametrized continuous periodic signals in a time inhomogeneous diffusion, (preprint), *arXiv:1003.3546v1 [math.ST]* 18 Mar 2010.
- R. Höpfner & Y. Kutoyants (2010), Estimating discontinuous periodic signals in a time inhomogeneous diffusion, (preprint), *arXiv:0903.5061v2 [math.ST]* 17 Mar 2010.
- A. Jankunas & R.Z. Khaminskii (1997), Estimation of parameters of linear homogeneous stochastic differential equations, *Stochastic. Process. Applications*, 72, 2956-219.
- I. Karatzas & S.E. Shreve (1991), *Brownian Motion and Stochastic Calculus*, Springer, New York.
- M.L. Kleptsyna & A. Le Breton (2002), Statistical analysis of the fractional Ornstein-Uhlenbeck type process, *Statist. Inf. Stochast. Proces.* 5, 229–248.
- Yu. A. Kutoyants (transl. 1984), *Parameter Estimation for Stochastic Processes*, Heldermann Verlag, Berlin.
- Yu. A. Kutoyants (1994), *Identification of Dynamical Systems with Small Noise*, Kluwer Academic Publishers, Dordrecht.
- R. Liptser & A. Shiryaev (ed. 2001), *Statistics of Random Processes, vol I+II*, Springer, New York, (1977, 1978).
- S. Meyn & R. Tweedie (1993), *Markov Chains and Stochastic Stability*, Springer.
- D. Revuz & M. Yor (1991), *Continuous Martingales and Brownian Motion*, Springer.